

AHC-0924

Fire Alarm Control Panels



General

Fire control panels AHC-0924 series 5 and 10 zones, produce alarms to alert the control panel operator and the residents when they receive a fire signal from a fire detector normally. They consist of two different display modes, i.e. individual zone lamps and trouble alarm lamps which can connect with the graphic display.

Features

- Zoned visual red alarm LED and red FIRE indicators
- Zoned visual yellow O/C fault LED.
- Continuous signal during alarm.
- Built-in battery charger.
- Low/No power and battery detection.
- Automatic loading and testing of battery.
- Battery lead reversal protection.
- Zone fire test and zone O/C fault test.
- Fire storage (Double check of the fire signal)
- Fire alarm and trouble buzzer.

Electrical

- Model: AHC-0924 5 , 10 zone
- Standard: Reply CNS.8877.Z2044
- Primary Power Source: 220 VAC, 50/60 Hz
- Secondary Power Source: 24 VDC. (Battery 2.1 Ah)
- Zone Power: 24 VDC. (18 VDC - 30 VDC)
- Zone EOL: 10K EOL (1/4 - 1/2W Resistor)
- Bell Power: 24 VDC. (1.0 amps)
- Panel Color: Ivory
- Dimensions (mm): 5 Zone: 300 x 360 x 90
 10 Zone: 300 x 460 x 90

Fire Storage (for double check)

